



*** Pioneer DJS software included!**
In addition to DJS software, the MEP-7000 can be used to control many popular DJ software programs.

MEP-7000

Professional Multi-Entertainment Player

defining the industry standard.

For all your product info, dealers and more: www.PioneerDJ.com 800-782-7210

MEP-7000 Professional Multi-Entertainment Player

FEATURES

Flexible Audio Format Playback

As well as playback of traditional audio compact discs, the MEP-7000 supports MP3¹/AAC/WAV²/AIFF² stored in USB memory devices, hard disc drive (HDD), CD-R/RW and DVD±R/RW, allowing for easy playback of existing music libraries and new digital downloads.

4.3-Inch Color LCD & Intelligent Graphical User Interface

In addition to the high-resolution 4.3-inch color LCD panel, an intelligent graphic user interface and rotary selector enables rapid track search through large collections of digital audio files. A play list function also speeds the track selection process for recalling frequently played songs.

DJS Auto Mix Function

An auto mix function automatically mixes playback of the tracks registered on the play list in four modes such as ECHO or ZIP. Audio is seamlessly beat matched and mixed on the fly.

Control Functions

The MEP-7000 includes Pioneer's DJS all-in-one DJ software application for playback from a Windows based computer (PC not included). When the system is connected to the DJS, no mouse or keyboard is required for navigation and DJ performance. The MEP-7000 also supports control of other software, such as SERATO Scratch LIVE⁴, without the need of the control discs. It can also act as a full MIDI controller for any MIDI-compatible PC application.

Scratch Jog Effect and Digital Jog Break

In addition to traditional scratching, the MEP-7000 also features two patterns of Scratch Jog Effects – BUBBLE⁵ and TRANS⁵. Three Digital Jog Break effects freely control the audio effects according to the rotation of the jog dial—JET⁶ / ROLL⁶ / WAH⁶—broadening the scope of any DJ performance.

Bright Organic Electroluminescence (OEL) Display

Two high-visibility OEL displays provide outstanding visibility for the pitch, playback time and position information. Together with its main 4.3-inch color LCD, the OEL display ensures smooth DJ play regardless of lighting conditions.

Other Functions:

- Karaoke Mode: Full support for CD+G playback for karaoke performance via the composite video-output.
- Library Function: Allows selection of tracks from various categories like genre, artist, etc., when using the unit with DJS or USB.
- Tempo Control Range: The user can choose among four pitch ranges available for the tempo slider: ±6%, ±10%, ±16%, and WIDE⁹.
- Pitch Bend Button: Enables fine adjustment of the track speed by simply pressing a button.
- Seamless Loop: Repeats looped audio without interruption. A loop can be set from as small as one frame up to an entire CD's length.
- Hot Loop: Restarts the loop seamlessly from its entry without interruption of the music.

For more information and streaming demo videos, visit www.pioneerdj.com/gear_MEP7000

¹MPEG-1 Audio Layer3, MPEG-2 Audio Layer3 LSF. Also capable of playing MP3 file stored on a device connected to a PC. ²Available only on USB storage device (USB memory, HDD, etc). WAV/AIFF recorded on a disc media cannot be played. ³Using software version 1.6000, the MEP-7000 can control Pioneer DJS. Further firmware and software updates will be available online. ⁴Support for more DJ software applications pending from other companies but Pioneer does not guarantee the performance of software on users' computers. Scratch LIVE is a registered trademark of Serato Audio Research. ⁵BUBBLE: Simulates a "flare"-type scratch performed on a turntable. TRANS: A transform-effect which rhythmically cuts the audio. ⁶JET: A flanging effect similar to an offset playback using two analog records. ROLL: Looping effect with pitch variation based on jog rotation. WAH: Variable frequency cut-off according to the rotation of jog dial. ⁷As of January 16, 2008, according to Pioneer. ⁸WIDE mode not available on MP3/AAC/WAV/AIFF. ⁹Depending on a computer specifications, it may occasionally be necessary to use provided auxiliary power cable.

SPECIFICATIONS

Control Unit

USB Terminal..... USB B terminal x1
Video Output TerminalMONITOR OUT (RCA)
Dimensions (without package)19.02" (W) x 3.3" (D) 5.23" (H)
Weight (without package) 3.7lbs

Drive Unit

Compatible MediaMusic CD, CD-R, CD-RW, DVD±R, DVD±RW,
.....DVD±R-DL, USB storage device (USB memory, etc)
Compatible File.....MP3, AAC, WAV (44.1kHz/16 bit), AIFF (44.1kHz/16bit)
File System Responding to USB Storage.....FAT12, FAT16, FAT32, HFS+
Frequency Response..... 4Hz-20kHz
Signal-to-Noise Ratio..... 115dB or more (JEITA)
Total Harmonic Distortion..... 0.006% or less (JEITA)
USB Terminal..... USB A terminal x2, USB B terminal x1
Audio Output TerminalAUDIO OUT x2 (RCA), DIGITAL OUT x2 (RCA)
Other Terminals CONTROL x2 (3/5mm mini plug), Remote Control

Audio Output Voltage2V RMS
Power Requirements AC 120V, 60Hz
Power Consumption..... 32W
Dimensions (without package)19.01" (W) x 12.79" (D) x 3.58" (H)
Weight (without package) 13.44lbs

DJ Software DJS System Requirements

Compatible OS..... Windows Vista/XP/2000
Compatible File..... MP3
CPUPentium-M 1.5GHz or better
Memory 512 MB or more (Windows Vista: 1GB or more)
HDD 250MB or more
Disc Drive CD-ROM/CD-DA playable
Display 1024 pixel x 768 pixel (XGA) or more,
.....and High Color (16bit or more)
Sound Card..... Sound card with 2 or more terminals
..... or external sound devices

Pioneer

Features and specifications subject to change without notification.

PIONEER CORPORATION
1-4-1 Meguro, MEGURO-KU, TOKYO 153-8654, JAPAN
TEL: 81-3-3495-5246 • FAX: 81-3-3495-9827

PIONEER ELECTRONICS (USA), INC.
2265 East 220th Street, Long Beach, CA 90810, U.S.A.
TEL: 800-421-1404 • FAX: 310-952-2990

PIONEER ELECTRONICS ASIACENTRE, PTE. LTD. (PAC Head Office)
253 Alexandra Road, #04-01, SINGAPORE 159936
TEL: 65-6427-1111

PIONEER EUROPE NV - MULTIMEDIA DIV. (PEE-London)
Pioneer House, Hollybush Hill, Stoke Poges Slough, SL2 4QP, UNITED KINGDOM
TEL: 44-1753-789-789

PIONEER CHINA HOLDINGS CO., LTD. (PCH)
18F New Hua Lian Mansion (West), 775 Huai Hai Zhong Road (M), Shanghai 200020, CHINA
TEL: 86-21-6431-4466

PIONEER HIGH FIDELITY TAIWAN CO., LTD. (PTC)
13th FL, No.44, Jhongshan N Road, Taipei City, 10448 TAIWAN
TEL: 886-2-2521-3588

PIONEER ELECTRONICS AUSTRALIA PTY. LTD. (PTY)
178-184 Boundary Road, Braeside, Victoria 3195, AUSTRALIA
TEL: 507-300-3900

PIONEER INTERNATIONAL LATIN AMERICA S.A. (PILASA)
Plaza Credicorp Bank, 14th Floor, Calle 50 No.120, Panama City 0816-01361, R.O., PANAMA
Tel: 507-300-3900